Date **Product Code**  Designer



# ARTIMA'/2 W-OBM BLUETOOTH

surface mounted wireless LED wallwasher



- Luminaire is equipped with a Xicato Bluetooth Low Energy Intelligent Driver, controllable via a smart device with iOS or Windows based apps. Features include
  - standard Bluetooth Wireless connectivity
  - addressable individually
  - on/off control
  - dimming to 0.1%
  - data collection and storage for operating history
  - direct listening to switches and sensors
  - embedded Eddystone, iBeacon and/or AltBeacon beacons
- The optical assembly consists of a hammer tone aluminum reflector and a 40° x 70° spread lens.
- Luminaire provides 385° horizontal rotation and vertical adjustment from 0° to 90°. Horizontal adjustment can be locked by tightening the upper collar clamp using a 1/8" hex key; vertical adjustment can be locked by tightening the lower collar clamp using a 3/32" hex key.
- For more information, click here.

Artima/2 W-OBM Bluetooth is a wallwasher designed for mounting on a 4" octagonal outlet box (by others). Luminaire is powered by a Cree chip-on-board LED and equipped with a Xicato intelligent driver (XID). See tables below for wattages and efficacies.

#### PRODUCT CODE

For complete product code, list basic unit and select one item from each following box.

Basic Unit	
Light Source Output (Lumens	s)
1500L 1500L / CRI 80+	not available with 5000K L12Anot available with 5000K L15A

Light Color
2700K 27K
3000K 30K
3500K 35K
4000K 40K
5000K not available with all Light Outputs (see above) 50K

Finish	
white: white paint, white lead cord, matte aluminum heat sink	WH
black: black paint, black lead cord, black heat sink	BL
Industrial Silver: silver paint, black lead cord, black heat sink	SI
custom color: include physical chip with order and select one from below	
white lead cord, matte aluminum heat sink	- CCW
black lead cord, black heat sink	- CCB
any other combination requires a special order	

### **Circuit Limitations**

Luminaire operates only on circuits with

- no dimmer on the circuit or -
- a 0-10V dimmer on the circuit.

#### **USB** Key

To address this fixture from a Windows-based PC, laptop or tablet, a USB key (dongle) is required. Contact factory for USB key.




# ARTIMA/2 W-OBM BLUETOOTH



# **APPLICATIONS**

**Luminaire is suitable for highlighting vertical surfaces** in museums, galleries, showrooms, residences, offices and stores.

Luminaire is **6** listed for Damp Location mounting on a standard 4" octagonal outlet box (by others).



## PHOTOMETRIC REPORT (tested per IESNA LM-79-2008)

🔄 Leading Testing Laboratories Report No. UT18050006-010a. Original test report furnished upon request.

Luminaire ...... surface-mounted LED wallwasher with internal reflector and lens and a specular hammer tone kicker reflector.

Lamp...... Cree LED 2000 lumens, 3000K CCT.


Lamp Life ......rated 50.000 hours based on L70/B50 criteria. LM80 report by LED manufacturer furnished upon request.

#### WALLWASH INFORMATION

Distance From	3' From Wall; 3' O.C. (2100 lumens)		3' 6"From Wall; 3' 6"O.C. (2100 lumens)	
Ceiling (Feet)	Below Fixture	Between Fixtures	Below Fixture	Between Fixtures
1	19	17	13	11
2	34	30	23	20
3	41	38	29	27
4	37	36	29	28
5	31	29	25	25
6	24	23	21	21
7	18	18	17	1 <i>7</i>
8	14	14	14	13
9	11	11	11	11
10	9	9	9	9
11	7	7	7	8
12	6	6	6	6

This table lists initial illuminance values at the center of a row of at least 5 fixtures with no contribution from ceiling or floor reflectance. Fixtures were modeled with maximum candlepower at 20° to 25° above vertical.

# CANDLEPOWER DISTRIBUTION



### LIGHT OUTPUT MULTIPLIER

(Based on 2000 lumens 80 CRI option)

LED Module Type	Light Output Multiplier
1500 Lumens 80 CRI (L15S)	0.76*
2000 Lumens 80 CRI (L20S)	1
1200 Lumens 98 CRI (L12A)	0.58*
1500 Lumens 98 CRI (L15A)	0.76*

\*estimated values

# **LUMINAIRE LIGHT OUTPUT AND EFFICACY**

LED Module Type	Luminaire Light Output	Luminaire Efficacy (Ims/watt)	System Wattage
1500 Lumens 80 CRI (L15S)	795*	57*	14
2000 Lumens 80 CRI (L20S)	1046	52	20
1200 Lumens 98 CRI (L12A)	607*	43*	14
1500 Lumens 98 CRI (L15A)	<i>7</i> 95*	40*	20

<sup>\*</sup>estimated values

### **STANDARD DRIVER INFORMATION** (UL Class 2, dry and damp location)

Voltage	120	277
Input Watts (L15S/L20S/L12A/L15A)	14/20/14/20	14/20/14/20
Input Current (A) (L15S/L20S/L12A/L15A)	12/.17/.12/.17	.05/.07/.05/.07
Output Current (mA)	500-700	500-700
Min. Power Factor	0.90	0.90
Operating Temperature Range (F)	-4 to 122	-4 to 122